



## SPIRALED Night Sensor A60 E27 4W (32W) 350lm 822 Clear

LED lempa

11337

BAI Spiraled Night Sensor GLS A60 E27 4W 2000K Gold 300lm (28W) 230V-240V 320° 60x105mm Day / Night Lux Sensor LED-lamp

Spiraled® lamp with a day/night sensor. The Spiraled® lamps are proof that the atmosphere and appearance of this beloved lamp can be perfectly imitated. The curled LED filaments ensure that the LED light bulb, in addition to light, brings a lot of atmosphere. The base of the lamp has a sensor that reacts to the light (not on artificial light). At dusk (<20 lux), the lamp switches on and as soon as the light reappears, the lamp goes into sleep mode. You can therefore just leave the lamp "on" and never have to think again "would I have left the lamps on"? This makes this LED lamp even more energy efficient and sustainable than it already is.

## KLASIFIKACIJA

Grupė	Lempos
Klasė	Šviesos diodų lempos
Pavadinimas	SPIRALED Night Sensor A60 E27 4W (32W) 350lm 822 Clear
Gamintojas	BAI
Serija	Spiraled Plus
Tipas	A60 Sensor
EAN	8714681457696
Gamintojo kodas	145769

## PARAMETRAI

Lizdas	E27
Lempos galia [W]	4 - 4
Nominali įtampa [V]	220 - 240
Įtampos tipas	AC
Nominali srovė [mA]	32 - 32
Lempos forma	Kriaušė
Spalvinė temperatūra [K]	2000 - 2000
Spalva	Auksinė

Spalvų atkūrimo koeficientas CRI	80-89
Šviesos srautas [lm]	300 - 300
Spalvinė temperatūra pagal EN 12464-1	Šiltai balta mažiau nei 3300 K
Lempos efektyvumas [lm/W]	75
Spinduliavimo kampas [°]	320 - 320
Diametras [mm]	60
Ilgis [mm]	105
Energetinio efektyvumo klasė	G
Energetinio efektyvumo indeksas (EEI)	0.11
Siūlelinio tipo leputės	Taip
Energijos sąnaudos 1000 h [kWh]	4
Vidutinis tarnavimo laikas [h]	15000
Spalvos atitikimas (McAdamo elipsė)	SDCM6
Korpuso spalva	Nespalvotas
Apsaugos klasė (IP)	IP20
Reguliuojama	Ne
Paskirtis	A tipo
Minimalus įjungimo ciklų skaičius	12500
Fotobiologinė sauga pagal EN 62471	RG0
Galios faktorius	0.5
Valdymo galimybė	Ne
Stiklo gaubto tipas	Skaidri
Su nuotolinio valdymo pulteliu	Ne
Galimas IFTTT palaikymas	Ne
Suderinama su Amazon Alexa	Ne
Suderinama su Google Assistant	Ne
Suderinama su Apple HomeKit	Ne