

## EcoDim ED-10050 LED Driver/Trafo 7W 14-25VDC DIM 1-2 Spots

LED maitinimo šaltinis

12647



ECO DIM ED-10050 LED Driver/Trafo 5-7W 14-25VDC 200-240VAC Only for 1-2 Furniture spots Dimmable

With this dimmable LED driver/transformer from EcoDim you can switch on LED furniture spotlights with electricity. With this driver/transformer you can connect 1 or 2 furniture spots. The driver is supplied with a coupling block. Here you can easily plug in the plugs of the furniture spots. When you do not use a connection port, always put the supplied bridge in the relevant port that you do not use, so that the circuit is complete again. This dimmable LED transformer dims best with a phase-cutting LED dimmer (RC). You can order 145818 or 146004 as complementary article.

## KLASIFIKACIJA

|                 |                                                            |
|-----------------|------------------------------------------------------------|
| Grupė           | Apšvietimo valdymas                                        |
| Klasė           | LED maitinimo šaltiniai                                    |
| Pavadinimas     | EcoDim ED-10050 LED Driver/Trafo 7W 14-25VDC DIM 1-2 Spots |
| Gamintojas      | EcoDim                                                     |
| Serija          | LED Driver                                                 |
| Tipas           | 1/2 spots, 5-7W                                            |
| EAN             | 8719322372963                                              |
| Gamintojo kodas | ED-10050                                                   |

## PARAMETRAI

|                        |            |
|------------------------|------------|
| Išėjimo galingumas [W] | 7 - 7      |
| Ilgis [mm]             | 95         |
| Plotis [mm]            | 39         |
| Versija                | Impulsinis |
| Išėjimo įtampa [V]     | 14 - 25    |
| Išėjimo srovė [mA]     | 240 - 240  |
| Apsaugos klasė (IP)    | IP20       |
| Reguliavimas 0-10 V    | Ne         |

|                                           |                      |
|-------------------------------------------|----------------------|
| Reguliavimas 1-10 V                       | Ne                   |
| Reguliavimas DALI                         | Ne                   |
| Reguliavimas DMX                          | Ne                   |
| Reguliavimas DSI                          | Ne                   |
| Reguliavimas GPRS                         | Ne                   |
| Reguliuojantis tinklo jungiklis           | Ne                   |
| Tinklo įtampos reguliavimas               | Ne                   |
| Gamintojo pritemdymo sistema              | Ne                   |
| Krintančio fronto fazės reguliavimas      | Taip                 |
| Kylančio fronto fazės reguliavimas        | Ne                   |
| Integruotas reguliavimo potenciometras    | Ne                   |
| Reguliavimo programavimas                 | Ne                   |
| Reguliavimas radijo bangomis              | Ne                   |
| Sinusoidės amplitudės reguliavimas        | Ne                   |
| Reguliavimas prisilietimu                 | Ne                   |
| Reguliavimas mygtuku                      | Ne                   |
| Reguliavimas Zigbee                       | Ne                   |
| Aukštis [mm]                              | 23                   |
| Korpusas                                  | Plastikinis korpusas |
| Nėra reguliavimo                          | Ne                   |
| Elektrosaugos klasė                       | Nenurodyta           |
| Fiksuotos srovės                          | Taip                 |
| Fiksuotos įtampos                         | Taip                 |
| Tinka DC įėjimo įtampai                   | Taip                 |
| Tinka lauko sąlygoms                      | Ne                   |
| Galimas IFTTT palaikymas                  | Ne                   |
| Suderinama su Amazon Alexa                | Ne                   |
| Suderinama su Google Assistant            | Ne                   |
| Suderinama su Apple HomeKit               | Ne                   |
| Pastovaus šviesos srauto palaikymas (CLO) | Ne                   |