

T1 1/4 WE 6V 30mA C-2R

Lempa indikacijai ar signalizavimui

44189



BAI Subminiature Wire Ended T1 1/4 4.5x11.7mm 6V 30mA 0.03A 0.18W Clear 3000h C-2R Indication- and signalling lamp

As a specialist in this field, Bailey has built an extensive wide range of indication and signalling lamps over the many years being active in this industry. If Bailey doesn't know the lamp you're looking for it probably no longer exists. The subminiature types are the smallest lights. Applications: switches, control panels, signaling devices and automotive industry.

KLASIFIKACIJA

| | |
|-----------------|--------------------------------------|
| Grupė | Lempos |
| Klasė | Lempos indikacijai ir signalizavimui |
| Pavadinimas | T1 1/4 WE 6V 30mA C-2R |
| Gamintojas | BAI |
| Serija | Subminiature |
| Tipas | Wire ended |
| EAN | 8714681165553 |
| Gamintojo kodas | WE04060301 |

PARAMETRAI

| | |
|--------------------------|----------------------------|
| Lizdas | Vieliniai išvadai |
| Lempos galia [W] | 0.18 - 0.18 |
| Lempos įtampa [V] | 6 - 6 |
| Nominali srovė [mA] | 30 |
| Lempos forma | Vamzdis su jungtimi 1 gale |
| Spalvinė temperatūra [K] | 2700 |
| Spalva | Nenurodyta |
| Diametras [mm] | 4.5 |
| Bendras ilgis [mm] | 11.7 |

| | |
|--|----------------|
| Energetinio efektyvumo klasė | E |
| Ksenoninė | Ne |
| Kriptono lempa | Ne |
| Halogenų | Ne |
| Vidutinis tarnavimo laikas [h] | 3000 |
| Tinka rodyklėms | Ne |
| Tinka visakrypčiams mirksintiems šviestuvams | Ne |
| Tinka žibintuvėliams | Ne |
| Technologija | Kaitrinė lempa |