



## QuickFix 3+ 36V Power Supply Max 18W/500 LEDs

LED maitinimo šaltinis

28183

MK QuickFix 3+ 36V Power Supply Max 18W/500 LEDs

The choice of the suitable transformer (power supply) principally depends on the size of the installation, which is defined by the number of LEDs (200 max. points of light) or the total output. Our transformers allow an output of 7.2 watts and comply with protection class IP67. The transformers cannot be connected with Quick Fix® 230 Volt LED products, as this is prevented, as an additional precaution, by the Quick Fix® plug-in system of the 36V series.

## KLASIFIKACIJA

Grupė	Apšvietimo valdymas
Klasė	LED maitinimo šaltiniai
Pavadinimas	QuickFix 3+ 36V Power Supply Max 18W/500 LEDs
Gamintojas	MK
Serija	MK QuickFix
Tipas	MK Acc
EAN	9120079034544
Gamintojo kodas	002-009

## PARAMETRAI

Išėjimo galingumas [W]	18 - 18
Diametras [mm]	0
Ilgis [mm]	162
Plotis [mm]	35
Versija	Impulsinis
Apsaugos klasė (IP)	IP67
Aukštis [mm]	23
Korpusas	Metalinis korpusas
Elektroapsaugos klasė	Nenurodyta

Fiksuotos srovės	Taip
Fiksuotos įtampos	Ne
Tinka DC įėjimo įtampai	Ne
Tinka lauko sąlygoms	Taip