Product datasheet

OSRAM

ORIGINAL - FESTOON -

Original spare part





The cost-effective original spare parts

The ORIGINAL festoon lamps with OSRAM's reliable OEM quality can be used as original spare parts for a wide range of festoon lamps. The typical application areas of the lamps are number plate and side position lights as well as interior lighting and reading lights.

Product datasheet

Technical data

Product information

Order reference	6461	
Application (Category and Product specific)	Auxiliary lamp	


Electrical data

Power input	10 W
Nominal voltage	12.0 V
Nominal wattage	10.00 W
Test voltage	13.5 V
Power input tolerance	±10 %

Photometrical data

Luminous flux	105 lm
Luminous flux tolerance	±20 %

Dimensions & weight



Diameter	11.0 mm
Product weight	2.00 g
Length	36.0 mm

Lifespan

Lifespan B3	600 h
Lifespan Tc	1200 h

Additional product data

Base (standard designation)	SV8.5-8

Product datasheet

Capabilities

Technology	AUX		
Certificates & standards			
ECE category	-		
Country specific categorizations			
Order reference	6461		

Country specific information

Product code	METEL code	SEG-No.	STK-Number	UK Org
4008321094261	OSRA6461	-	-	-
4008321094278	OSRA6461	-	-	-
4008321094261	OSRA6461	-	-	-

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4008321094261	ORIGINAL FESTOON 6461	Unpacked 1	38 mm x 10 mm x 10 mm	0.00 dm ³	4.00 g
4008321094278	ORIGINAL FESTOON 6461	Folding carton box 10	54 mm x 40 mm x 138 mm	0.30 dm ³	43.10 g
4008321094285	ORIGINAL FESTOON 6461	Shipping carton box 50	205 mm x 144 mm x 64 mm	1.89 dm³	265.50 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.















