OSRAM

ORIGINAL - METAL BASE -

Original spare part

The cost-effective original spare parts for trucks

Discover OSRAM´s ORIGINAL signal lamps with metal bases - high-quality original spare parts for 24 volt lamps. Due to the wide product range, the lamps can be used for different applications: as position and parking lights, indicator, brake, fog and reversing lights as well as number plate and side position lights.

Product datasheet

Technical data

Product information

Order reference	7529
Application (Category and Product specific)	Auxiliary lamp

Electrical data

Power input	15 W
Nominal voltage	24.0 V
Nominal wattage	15.00 W
Power input tolerance	±10 %
Test voltage	28.0 V

Photometrical data

Luminous flux	210 lm
Luminous flux tolerance	±25 %

Dimensions & weight

Length	46.5 mm
Diameter	25.0 mm
Product weight	7.98 g

Lifespan

Lifespan B3	100 h
Lifespan Tc	300 h

Additional product data

Base (standard designation)	BA15s

Capabilities

Technology	AUX

Certificates & standards

ECE category	-

Country specific categorizations

Order reference	7529

Country specific information

Product code	METEL code	SEG-No.	STK-Number	UK Org
4050300891774	OSRA7529	-	-	-
4050300891781	OSRA7529	-	-	-
4050300891774	OSRA7529	-	-	-

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4050300891774	ORIGINAL - METAL BASE 7529	Unpacked 1	- x - x -		
4050300891781	ORIGINAL - METAL BASE 7529	Folding carton box 10	58 mm x 54 mm x 139 mm	0.44 dm³	101.70 g
4008321091048	ORIGINAL - METAL BASE 7529	Shipping carton box 50	273 mm x 145 mm x 65 mm	2.57 dm³	558.50 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.

OSRAM